

June 10, 2022 | V 1.0

Software Function Guide

TN059S-E

LINE Notify Service

Overview

Cermate HMI/Protocol Gateway/PanelExpress support the connecting with LINE Notify service. After complete the connection setting, Cermate products can use the “LINE Notify” official account to send notification messages. Following is the setting steps.

NOTE: The Instant Message sending function of Cermate products is based on the LINE Notify service. If the LINE Corporation ends the LINE Notify service, the message sending function may risk not being able to work appropriately.

Cermate Products

HMI: PK2(Ethernet)/PT2/PX/IT4/PM2/SPK2(Ethernet)/SPT2/SIT4/SPM2 Series

Protocol Gateway: ES/SES Series

SCADA: PanelExpress v4.0

Software

OS: Windows 7 (64 bit)/Windows 10(64 bit)

PM Designer: PM Designer v4.0.7.03 or higher version

Software Download Link

Please contact Cermate representative for the latest PM Designer.

PM Designer v4.0 Setting

- (1) Please register Cermate Products(HMI/Protocol Gateway/PanelExpress) to IDCS. (Please refer to IDCS related documents for more details.)
- (2) Go to IDCS website


Welcome to use IDCS

Account

User


User Password

Click or touch the: **Computer**



[Forgot Password?](#)

- (3) Go to “My Profile” and “Get Line Token”
 LINE website: <https://notify-bot.line.me/>



Navigation: Welcome | Users | Devices | Sessions | Operation Logs | **My Profile** | Buy Points | Points Usage

Left sidebar: | |

Change Profile

User Name:

Account:

Level:

Email:

Company Name:


Mobile Number:

[Country/Region Codes List](#)


Wechat Notify Uri:

Line Token:

(4) Go to LINE Notify, log in your account and click “My page”.



(5) Click “Generate token”




(6) Enter token name and notification group name.

Generate token ✕

Please enter a token name to be displayed before each notification.

Select a chat to send notifications to.

-  1-on-1 chat with LINE Notify

(7) Copy the token you received and paste to IDCS website “My Profile” page in “Line Token”.

Your token is:

5EhqATHXH2E8Hg79bf0EWg5n9coxW8GkqNqEv

If you leave this page, you will not be able to view your newly generated token again. Please copy the token before leaving this page.

CopyClose



SessionsOperation LogsMy ProfileBuy

Change Profile

User Name	<input type="text" value="Hank"/>
Account	<input type="text" value="CermateHank"/>
Level	<input type="text" value="8"/>
Email*	<input type="text" value="hank.lin@cermate.com"/>
Company Name	<input type="text" value="N/A"/>
Mobile Number*	<input type="text" value="886"/> <input type="text" value="0987737917"/>
<small>Country/Region Codes List</small>	
Wechat Notify Uri	<input type="text" value="URL"/>
Line Token	<input type="text" value="KkHXhatS6XstGemFQGJM70BZOTUjfeSVzCyy4ItE"/>
<small>Get Line Token</small>	

(8) Go to “Devices”, select Device (in Device Group List) that sends LINE Notify message, then “Edit” and select “App Notification Setting”.

NOTE: You must have Device Admin authorization.





(9) In “App Notification Setting”, you can add users to receive notification.


(10) PM Designer Setting

- (A) Go to “Alarm” and “Add Discrete Alarm Block”
- (B) Key in notification wording in “Message”
- (C) Enable “Send Short Message Via IDCS”
- (D) Define Message Type (Alarm...)

- (E) "Send Windows Screen Image": Besides message, you can also save image as file and send as notification
- (F) "Send Also When Alarm Is Cleared": When alarm is released, you can receive notification



(11) LINE Notify push notification





Technical Support Information

Website www.cermate.com

Quick contact information overseas
jay.wei@cermate.com